

## 9. Tabela 2. Zestawienie ilości opraw oświetleniowych

lp	nr pom	typ oprawy	oznaczenie	ilość
POZIOM -1				
1	0.4	REGLUX 1040.LED 6000lm 50W IP44	G1.1	4
2	0.5	REGLUX 540.LED 3200lm 30W IP44	I1.1	2
3	0.6	REGLUX 540.LED 3200lm 30W IP44	I1.1	6
4	0.7	REGLUX 540.LED 3200lm 30W IP44	I1.1	6
5	0.8	REGLUX 540.LED 3200lm 30W IP44	I1.1	1
6	0.9	REGLUX 540.LED 4300lm 40W IP44	H1.1	1
		OP1-A1,2TA1N	EW1.1	1
		OP20-A1,2TA1N IP65	AW2.1	1
7	0.10	S4000 2035.LED 4100lm 43W	J1.1	3
8	0.11	REGLUX 540.LED 3200lm 30W IP44	I1.1	2
9	0.12	REGLUX 540.LED 3200lm 30W IP44	I1.1	3
		OP20-A1,2TA1N IP65	AW2.1	1
10	0.13	AMARO 3000lm 45W IP44	C1.1	3
		POINT LED 1,5W	AW1.1	3
		OP1-A1,2TA1N	EW1.1	1
11	0.3	AMARO 3000lm 45W IP44	C1.1	2
		POINT LED 1,5W	AW1.1	2
		OP1-A1,2TA1N	EW1.1	1
12	klatka schodowa	AMARO 3000lm 45W IP44	C1.1	1
		POINT LED 1,5W	AW1.1	1
		OP1-A1,2TA1N	EW1.1	1
POZIOM 0				
lp	nr pom	typ oprawy	oznaczenie	ilość
13	1.4	S4000 2035.LED 4100lm 43W	J1.1	8
14	1.5	ANGLE 2025. 8900lm 87W	A1.1	6
15	1.6	REGLUX 540.LED 3200lm 30W IP44	I1.1	4
		OP20-A1,2TA1N IP65	AW2.1	1
		OP1-A1,2TA1N	EW1.1	1
18	1.7	REGLUX 540.LED 3200lm 30W IP44	I1.1	4
		OP20-A1,2TA1N IP65	AW2.1	1
		OP1-A1,2TA1N	EW1.1	1
21	1.8	TITANIA 4600lm 46W	F1.1	4
22	1.9	REGLUX 540.LED 4300lm 40W IP44	H1.1	2
23	1.10	MODERNA 2N 4100lm 35W	D1.1	3
24	1.11	AMARO 3000lm 45W IP44	C1.1	3
		POINT LED 1,5W	AW1.1	2
		OP1-A1,2TA1N	EW1.1	1
25	wejście	GFMW LED 23W IP65	L1.1	2
		OP2-A1,2TC1N IP65	EW2.1	1
26	1.12	AMARO 3000lm 45W IP44	C1.1	3
		POINT LED 1,5W	AW1.1	3

		OP1-A1,2TA1N	EW1.1	1
27	1.13	REGLUX 1040.LED 6000lm 50W IP44	G1.1	4
28	1.3	AMARO 3000lm 45W IP44	C1.1	3
		POINT LED 1,5W	AW1.1	2
		OP1-A1,2TA1N	EW1.1	1
POZIOM 1				
lp	nr pom	typ oprawy	oznaczenie	ilość
29	2.4	MODERNA 2N 4100lm 35W	D1.1	4
30	2.5	REGLUX 540.LED 3200lm 30W obrót 90° IP44	I1.2	2
31	2.6	AMARO 3000lm 45W IP44	C1.1	4
32	2.7	TITANIA 4600lm 46W	F1.1	2
33	2.8	REGLUX 540.LED 3200lm 30W obrót 90° IP44	I1.2	2
34	2.9	MODERNA 2N 4100lm 35W	D1.1	4
35	2.10	ARCH FLOWER 9200lm 100W	B1.1	4
36	2.11	REGLUX 540.LED 3200lm 30W obrót 90° IP44	I1.2	2
		OP20-A1,2TA1N IP65	AW2.1	1
		OP1-A1,2TA1N	EW1.1	1
37	2.12	AMARO 3000lm 45W IP44	C1.1	7
		POINT LED 1,5W	AW1.1	3
		OP1-A1,2TA1N	EW1.1	2
38	2.13	ARCH FLOWER 9200lm 100W	B1.1	4
39	klatka schodowa	AMARO 3000lm 45W IP44	C1.1	3
		POINT LED 1,5W	AW1.1	3
40	2.3	AMARO 3000lm 45W IP44	C1.1	2
		POINT LED 1,5W	AW1.1	2